


Original Operating Manual:

Photoelectric sensors with analog output: IRS/IRN/IRD-010-LA*(-OP)

IRD-010-LA*-OP

Housing M30

IRN-010-



- Also for using with different certificated fibre optics
- IRD: ATEX and IECEx certificated
- Types IRD: For use in Ex Zones (0), 1, 2, (20), 21, 22
- Types IRN: For use in Ex Zones (1), 2, (21), 22
- With voltage or current loop output available
- Applicable for range measurement or position detection
- Applicable with glass fibre optics



ATEX-Kennzeichnung:

II 3(2)G Ex nA [op is Gb] IIB T4 Gc, II 3(2)D Ex tc [op is Db] IIIA T135°C Dc

Technical data	Type		
	IRS-010-LA*	IRN-010-LA*-OP	IRD-010-LA*-OP
<p>LA*= Type of analog output. LAV: Voltage output 0 ... 10V. LAI: current loop output 0mA ... 20mA. LA4: current loop output 4mA ... 20mA</p>			
Type of Ex protection Gas, according to 2014/34/EU	NONE	II 3(2)G Ex nA [op is Gb] IIB T4 Gc	II 2(1)G Ex d [op is Ga] IIC T6 Gb
Type of Ex protection Dust, according to 2014/34/EU	NONE	II 3(2)D Ex tc [op is Db] IIIA T135°C Dc IP67	II 2(1)D Ex tb [op is Da] IIIB T100°C Db IP67
For use in Ex Zones	NONE	Zones (1), 2, and (21), 22	Zones (0), 1,2 and (20), 21, 22
Output signal range	0.03VDC - 10.5VDC (Ripple: <20mV) or 0.06mA - 21mA or 4mA - 20mA		
Voltage output, nominal range, on white paper. A4. 80g	5VDC output voltage at a distance of 1m, adjustable		
Current output, nominal range, on white paper. A4. 80g	10mA output current at a distance of 1m, adjustable		
Light source	Infrared 870nm		
Optical angle	approx. 10°		
Maximum optical radiant power	NOT LIMITED	<=35mW	<=15mW
Maximum radiant power	NOT LIMITED	<=5mW/mm²	<=5mW/mm²
Response time	5ms (faster response time, on request)		
Power up delay time	500ms		
Supply voltage	24VDC +/-10%, Um = maximum 30VDC		
Intrinsic current consumption	max. 60mA		
Maximum power dissipation	2.1W		
Output type, voltage, IR*-010-LAV(-OP)	PNP, output impedance appr. 25Ω, RLoad: 2kΩ to 1MΩ		
Output type, current, IR*-010-LAI/LA4(-OP)	NPN, output impedance appr. 500Ω, RLoad: 0Ω to 100Ω		
Disable-Input, only types IR*-010-LA*(-OP)-S259	PNP compatible, Ri 10kΩ		
Housing	M30, brass Ms 58, nickel plated (optional stainless steel 1.4404, types: IR*-002-A*(-OP)-S224		
Enclosure rating, according to EN 60529	IP 65	IP 67	IP67
Ambient working temperature range Tamb	-20°C up to +50°C		
Storage temperature range	-20°C ... +70°C		
Relative humidity	15% ... 80%		
Vibration and shock resistance	Vibration: 30g over 20Hz to 2kHz. Shock: 100g for 3ms		
Pollution degree, according to EN 60664-1:2007-4	R3A30AP1		
Device designation, according to EN 60947-5-2	R3A30AP1		
Connection cable	3+PE x 0,5mm², TPU, shielded, leads numbering marked, oil resistant cable for trailing, L: 3m		
Connection cable, types IR*-010-LA*(-OP)-S259	4+PE x 0,5mm², TPU, shielded, leads numbering marked, oil resistant cable for trailing, L: 3m		
Socket, IRS/IRN-010-LA*(-OP)-S099	Male connector M12, Lumberg RSF 5, 5-leads		
Accessories, all devices	- 2x nuts M30 (or 1 clamp on demand)		
Accessories, only IRD/IRN-010-LA*-OP	- 1x Spare safety screw with packing ring for potentiometer sealing		
Accessories, only IRN-010-LA*-OP-S099	- 1x Safety lock device, mount at the cable connection, for locking the connection		
	- 1x Warning plate "Do not open/close when supply voltage connected"		
	- 1x Protection cap for the sensor socket		
Accessories, not included, only IRS/IRN*-S099	- Single ended cordset, types RKTS 5-298/xx or RKWTH 5-298/xx, Lumberg		
Options	- Cable length: Up to maximum 100m. Designation: IR*-010-LA*(-OP)/K:100m - IRS/IRN-010-LA*(-OP)-S099: Male connector M12: Lumberg RSF-5, 5 pins - IRS/IRN-010-LA*(-OP)-S193: Replacement for series IRS-U-10A/I-GF, for applications with fibre optics series ...Y1.... (Special adoption) - IRN/IRD-010-LA*(-OP)-S224: Housing stainless steel 1.4404 / 316L - IR*-010-LA*(-OP)-S259: With emitter disable input (DI)		
Function and LED indication	Light barrier with fibre optic Proximity switch Proximity switch with fibre optic The brightness of the LED and the output level, is dependant on the quantity of the detected light.		
			No light detected. Output=OFF, LED=OFF
Wiring and connection			
Output diagram (measured on white paper, 80g, 20cmx30cm) Potentiometer on MAXIMUM			

